



WAH-WAH PEDAL

V846

Digital rendering, additions, and corrections copyright 2000 North Coast Music. All rights reserved, unauthorized duplication or resale strictly prohibited.

SERVICE INFORMATION

Thomas Organ Company • National Service Department • Sepulveda, California

REPLACEMENT PARTS LIST

CAPACITORS

Location	Part No.	Description
C1-C4	09-5901-0	.01 uF 125V 10%
C2	09-5902-0	4 uF 18V (N. P. Electro.)
C3-C5	09-5903-0	.22 uF 200V 10%

RESISTORS: All 1/2W 10% Unless Otherwise Indicated

R1	60-10401	100 k Ohm
R2	60-68301	68 k Ohm
R3	60-15201	1.5 k Ohm
R4-R7	60-47401	470 k Ohm
R5	60-47101	470 Ohm
R6	60-22301	22 k Ohm
R8	09-5904-0	100 k Ohm Exp. Ped. Pot. W/Gear
R9	60-10201	1 k Ohm
R10	60-10301	10 k Ohm

MISCELLANEOUS

B1	66-5000-0	9V Battery
J1	09-5907-0	Phone Jack - Double Circuit
J2	09-5908-0	Phone Jack - Single Circuit
L1	09-5905-0	Inductor - 500 mH
Q1-Q2	Use 86-5044-2	Transistor (2N3900A)

